




***dogtra* RR Deluxe
Code Setting Guide**

A large, faint, light gray watermark of a dog's head profile is visible in the background, centered horizontally and extending across the bottom half of the page.


www.dogtra.com

Code setting method to pair a transmitter with receivers


dogtra RR Deluxe uses code free technology so that you can match one transmitter up to eight different receivers. (16 including left and right ports) Once the code has been set, pressing a button on the specific selection dial will only activate the designated receiver. Follow the steps in order to pair a transmitter with a receiver unit.



- 1) Turn the selection dial of handheld transmitter to the desired number to pair it with the receiver. (For example, if you want to designate a receiver as your number 2 receiver, set the selection dial of the transmitter to number 2.)



- 2) Hold down the on/off button of the receiver for 5 seconds or more. Release them when the green LED blinks rapidly.



- 3) Within 5 seconds after releasing the on/off button of the receiver, hold the left and right buttons simultaneously on the handheld transmitter. When the receiver successfully acknowledges the transmitter, the LED on the receiver should emit a constant green light for approximately 3 seconds then switch to slow steady standby blink.
- 4) Press the duck call or beep sound button on the transmitter. If the receiver emits sound, the receiver is successfully coded to the transmitter. (Repeat the process from step 1, if you have additional receivers to be coded.)



Dogtra Company

22912 Lockness Avenue
Torrance, CA 90501 U.S.A.

Tel) 310.534.0101

Fax) 310.534.9111

Toll free) 1.888.811.9111

Store website) shop.dogtra.com